



JellyFish Lighting Zone

Compatible Control4 Systems:

Designed to work with Control4 2.10.x, Control4 3.x.

Compatible Hardware:

[JellyFish Lighting](#)

Documentation, Driver Download & Change Log:

<https://drivercentral.io/platforms/control4-drivers/lighting/jellyfish-lighting>

Installation/Integration Support

Please contact manufacture directly: [JellyFish Help Center](#)

Content

- [Overview](#)
- [Setup](#)
- [Properties](#)
- [JellyFish Zone Settings](#)
- [Extras View](#)

- [Connections](#)
 - [Events](#)
 - [Actions](#)
 - [Variables](#)
 - [Dealer Notes](#)
 - [Warranty & Disclaimer](#)
 - [Developer Information](#)
-

Overview

JellyFish Lighting makes premium permanent outdoor lighting that immediately adds curb appeal and character to your home or business! The system is capable of being used for nightly accent lighting that can also be a light source for your security cameras, or change to festive decorations for your favorite holidays and events with a few quick button clicks. Now you can easily manage JellyFish Lighting with your Control4 system with this Cindev created driver!

Setup

- Set up lighting zones prior to installation of the driver using the native application
- Install the controller driver
- Use the Network tab (under Composer's Connections section) to enter the IP address of the controller
- Verify that the driver property *Connection* is showing *Online* and that the *Name* and *Version* properties are populated
- Install a zone driver for each zone found in the controller
- Bind each zone driver to the zones listed under the controller's Connections
- Verify that the *Zone Name* property in the zone driver populates with the correct zone name
- Select the Extras View to be used by the zone

- Set up programming as needed

Properties

- *Driver Status*: Displays driver related information
- *Driver Version*: Displays driver version
- *Debug Mode*: Displays additional information on the lua tab for debugging purposes


JellyFish Zone Settings

- *Zone Name*: Displays the name of the connected zone
- *Selected Pattern*: Displays the selected pattern on the zone
- *Extras View*: Select the lighting extras interface to use. See section below for more details.

Extras View

The driver comes with two separate lighting extras interfaces. They both have serve the same function though the experience differs a bit.

- *Folder*: Pattern selection is broken down by folders that contain respective patterns



- *Select*: Pattern selection is done in a single field that contains all patterns

4:04



Extras


JELLYFISH ZONE: SMALL

Sync Zones

Selected Pattern

Christmas/Mint





Both views contain a Sync Zones button which matches all zones of the JellyFish controller to the selected pattern on this zone

Connections

- *JF_ZONE*: Connects to the JellyFish controller driver

Events

- *Pattern Selected*: When the pattern is selected

Actions

- *Select Pattern*: Select the JellyFish pattern

- *Sync Zones*: Match all zones of the JellyFish controller to the selected pattern on this zone

Variables

- *Selected_Pattern* (STRING)
 - The current selected pattern as seen in the *Selected Pattern* driver property

Dealer Notes

Both *Sync Zones* and *Select Pattern* commands will turn the lights to the *On* state, regardless of the current state.

Warranty & Disclaimer

<https://jellyfishlighting.com/faq/> See *What is the warranty?* section

Developer Information

brought to you by:
Cinegration Development, LLC



www.cindev.com
www.drivercentral.io/cinegration/

We are always looking to improve our drivers.
Please send your suggestions to: info@cindev.com