

Notes:

- THIS DRIVER DOES NOT CONTROL THE NILES ZR-4630. The ZR-4630 is an IR only system.
- There is a switch on the front of the Niles ZR6 to allow the front RS232 jack to be used for uploading a project. Make sure this connection is set to 'NORMAL'
- Control4 RS232 DB9-> 1/8" Mini cables need to have pins 2/3 reversed for proper RS232 setup.

Purpose of Driver:

Many existing homes had sound systems that have Niles ZR-6 equipment in them. This driver allows a dealer to integrate up to 18 zones of audio via 1 RS232 port on any control4 system.

Driver Features:

- ▲ Niles ZR-6 Feature
 - 2 Way Volume Feedback (note: set volume is not allowed as Niles doesn't support it)
 - 2 Way Mute and Power Feedback
 - Polling of Active Zones so dealers can keep customers existing niles keypads for audio support
 - Direct Tuner Control for Both AM and FM

Installation Procedure:

Dealers need to install the Niles ZR-6 first and verify functionality before implementing this driver.

- ▲ Niles Setup
 - Connect a DB-9 to 1/8" Stereo Plug from any Control4 RS232 port to the RS232 jack on the Niles piece.
 - Record Zones and Sources on the equipment
- ▲ Control4 Setup
 - Add Niles driver (under Receivers, Manufacture Niles) to the system and 'bind' the zones and sources to their corresponding equipment
 - Under the properties menu, choose how many zones of audio the ZR-6 is using (this property determines which zones the Control4 will poll)
 - Connect the serial port to the driver
- ▲ Once this is done the driver should be ready for deployment.
 - You will know the driver is communicating with the ZR-6 when the Driver Information tab displays "Niles Communcion Good" with a firmware of the unit
- ▲ Notes on the AM/FM Radio
 - The tuner is a toggling input between AM and FM. Pressing AM or FM via a Control4 screen will toggle between inputs. You can also press the 'SELECT' button on a Control4 SR250 remote to do this also
 - Direct Tuning support is available and is available via pressing number buttons on

either a Control4 screen or a SR250

- If you are on AM you must enter a 4 digit number for the command to work (e.g. 0850 for 850AM)
- If you are on FM you only need to enter the numbers for the station (e.g. 973 for 97.3FM or 1067 for 106.7FM)
- This driver does support Station media via the Media Tab in Composer.
 - To use this, click on the AM or FM cloud in Medai and press New
 - Enter at least the name and the Station (station format will be as follows, XXXXAM for am and XXX.XFM for FM where X is a number)
 - Click OK

Notes:

- ⤴ This driver does not control any iPod connected to the ZR-6 directly. It can however, choose that input and control volume etc...
- ⤴ This driver contains code written by Cinegration. Any modification to this driver or any driver written by Cinegration without the express consent will void all warranties, constitute a ban on all drivers released by Cinegration and potentially legal action.
- ⤴ This driver has been designed to work with Control4® 2.6.0 System

Warranty:

Cinegration strives to provide fully working drivers without defects. However, changes and bugs may be found. Because of this, any bug/maintenance update to this driver will be free of charge. However, due to the ever changing nature of computer and audio/video systems, if a new version of the Control4® software creates issues with this driver, or feature enhancements, an upgrade version will be provided for an additional expense or free as determined by Cinegration LLC.

Thank you for choosing a driver By: Cinegration LLC.